



F&F Filipowski sp. j.
ul. Konstantynowska 79/81
95-200 Pabianice POLAND
tel/fax 48 42 2270971
e-mail: fif@fif.com.pl

AS-213

STAIRCASE TIMERS



www.fif.com.pl

F&F products are covered by an 24 months warranty from date of purchase

PURPOSE

Staircase timer AS-213 serves to keep switched-ON lighting of staircase, corridor, or any other object for the set time and to switch-OFF this lighting automatically, upon elapse of this set time.

FUNCTIONING

Turned ON staircase timer supports the lighting during set time by potentiometer (from 0,5min. to 10min.). After passage of set time timer will switch OFF the lighting automatically. After switching OFF the lighting there is possibility to switch it ON again.

Function of counter blockade does not allow to keep the light-ON in case of staircase switch blocking (after blocking the pushbutton, for example by match, the timer will count the set time and switch OFF the lighting). Next switching ON can be after removing the blockade.

ASSEMBLY

1. Take OFF the power.
2. Put on the relay on the rail in switchgear box.
3. Connect the relay to circuitry with wiring diagram.
4. By flat screwdriver set to switching threshold.


ATTENTION!

AS-213 is adapted to co-operate with pushbuttons equipped with neon lamp.


TECHNICAL DATA

supply	230VAC
current load	<16A
switching OFF delay (to set)	0,5÷10min
switching ON delay	<1sec
connection	screw terminals 2,5mm ²
power consumption	1,2W
working temperature	-25÷50°C
dimensions	2 modules (35mm)
fixing	on the rail TH-35

WIRING DIAGRAM



3 wires connection
A090330



4 wires connection